

LM108

OPERATIONAL AMPLIFIER

Industry Part Number

LM108

Prime Die

LM108

Processing	Subgrp	Description	Temp (°C)
MIL-STD-883, Method 5004	1	Static tests at	+25
	2	Static tests at	+125
	3	Static tests at	-55
Quality Conformance Inspection	4	Dynamic tests at	+25
	5	Dynamic tests at	+125
	6	Dynamic tests at	-55
	7	Functional tests at	+25
	8A	Functional tests at	+125
	8B	Functional tests at	-55
	9	Switching tests at	+25
	10	Switching tests at	+125
MIL-STD-883, Method 5005	11	Switching tests at	-55

Rochester Ordering Guide

**Most products can also be offered as RoHS compliant, designated by a -G suffix. Please contact factory for more information.*

Rochester Part Number	OCM Part Number	Package	Temperature
LM108H	LM108H	CAN-8, Metal	-55° to +125°C
LM108H/B	LM108H/883	CAN-8, Metal	-55° to +125°C
LM108JG-8/B	LM108JG-8/883	CDIP-8	-55° to +125°C
LM108J	LM108J	CDIP-14	-55° to +125°C

**For complete Rochester ordering guide, please refer to page 2.
Please contact factory for specific package and specification availability.**

Rochester Electronics guarantees performance of its semiconductor products to the original OEM specifications. "Typical" values are for reference purposes only. Certain minimum or maximum ratings may be based on product characterization, design, simulation, or sample testing. Rochester Electronics reserves the right to make changes without further notice to any specification herein.

LM108

Electrical Characteristics

DC PARAMETERS

(The following conditions apply to all the following parameters, unless otherwise specified.)

DC: $V_{CC} = \pm 20V$, $V_{CM} = 0V$

SYMBOL	PARAMETER	CONDITIONS	NOTES	PIN-NAME	MIN	MAX	UNIT	SUB-GROUPS
Vio	Input Offset Voltage	$V_{CM} = -15V$			-2.0	2.0	mV	1
					-3.0	3.0	mV	2, 3
		$V_{CM} = 15V$			-2.0	2.0	mV	1
					-3.0	3.0	mV	2, 3
		$V_{CC} = \pm 5V$			-2.0	2.0	mV	1
					-3.0	3.0	mV	2, 3
Iio	Input Offset Current	$V_{CM} = -15V$			-0.2	0.2	nA	1
					-0.4	0.4	nA	2, 3
					-0.2	0.2	nA	1
					-0.4	0.4	nA	2, 3
		$V_{CC} = \pm 5V$			-0.2	0.2	nA	1
					-0.4	0.4	nA	2, 3
Iib+	Input Bias Current	$V_{CM} = -15V$			-0.1	2	nA	1
					-1.0	3.0	nA	2, 3
		$V_{CM} = 15V$			-0.1	2	nA	1
					-1.0	3.0	nA	2, 3
		$V_{CC} = \pm 5V$			-0.1	2	nA	1
					-0.1	3.0	nA	2, 3

LM108

Electrical Characteristics

DC PARAMETERS (Continued)

(The following conditions apply to all the following parameters, unless otherwise specified.)
 DC: $V_{cc} = \pm 20V$, $V_{cm} = 0V$

SYMBOL	PARAMETER	CONDITIONS	NOTES	PIN-NAME	MIN	MAX	UNIT	SUB-GROUPS
Iib-	Input Bias Current	$V_{cm} = -15V$			-0.1	2	nA	1
					-1.0	3.0	nA	2, 3
		$V_{cm} = 15V$			-0.1	2	nA	1
					-1.0	3.0	nA	2, 3
		$V_{cc} = \pm 5V$			-0.1	2	nA	1
					-1.0	3.0	nA	2, 3
PSRR	Power Supply Rejection Ratio	$\pm 20V \leq V_{cc} \leq \pm 5V$			80		dB	1, 2, 3
CMRR	Common Mode Rejection Ratio	$-15V \leq V_{cm} \leq 15V$			85		dB	1, 2, 3
Ios+	Short Circuit Current	$V_{cc} = \pm 15V$			-30	-1.0	mA	1, 2, 3
Ios-	Short Circuit Current	$V_{cc} = \pm 5V$			1	30	mA	1, 2, 3
Icc	Power Supply Current					0.6	mA	1
						0.4	mA	2
						0.8	mA	3
Rin	Input Resistance		2		30		MOhm	1

LM108

Electrical Characteristics

DC/AC PARAMETERS

(The following conditions apply to all the following parameters, unless otherwise specified.)

DC: $V_{cc} = \pm 20V$, $V_{cm} = 0V$

AC: $V_{cc} = \pm 20V$, $V_{cm} = 0V$

SYMBOL	PARAMETER	CONDITIONS	NOTES	PIN-NAME	MIN	MAX	UNIT	SUB-GROUPS
Vin	Input Voltage Range	$V_{cc} = \pm 15V$	1		± 14		V	1, 2
		$V_{cc} = \pm 15V$	1		± 13.5		V	3
			1		± 15		V	1, 2, 3
Delta Vio/Delta T	Temperature Coefficient of Input Offset Voltage	$25C \leq TA \leq +125C$	4			15	$\mu V/C$	2
		$-55C \leq TA \leq 25C$	4			15	$\mu V/C$	3
Delta Iio/Delta T	Temperature Coefficient of Input Offset Current	$25C \leq TA \leq +125C$	4			2.5	$\mu A/C$	2
		$-55C \leq TA \leq 25C$	4			2.5	$\mu A/C$	3
Vop+	Output Voltage Swing	$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$			13		V	4, 5, 6
Vop-	Output Voltage Swing	$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$				-13	V	4, 5, 6
Avs+	Open Loop Voltage Gain	$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$, $V_{out} = 0 \text{ to } 10V$	3		50		V/mV	4
		$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$, $V_{out} = 0 \text{ to } 10V$	3		25		V/mV	5, 6
Avs-	Open Loop Voltage Gain	$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$, $V_{out} = 0 \text{ to } -10V$	3		50		V/mV	4
		$V_{cc} = \pm 15V$, $R_l = 10K \text{ Ohms}$, $V_{out} = 0 \text{ to } -10V$	3		25		V/mV	5, 6
TR(tr)	Rise Time		2		1		μS	7
TR(os)	Overshoot		2			30	%	7

DC PARAMETERS: DRIFT VALUES

(The following conditions apply to all the following parameters, unless otherwise specified.)

DC: $V_{cc} = \pm 20V$, $V_{cm} = 0V$. "Deltas not required on B-Level product. Deltas required for S-Level product ONLY as specified on Internal Processing Instructions (IPI)."

Vio	Input Offset Voltage	$V_{cm} = 15V$			-0.5	0.5	mV	1
Iib+	Input Bias Current	$V_{cm} = 15V$			-1	1	nA	1
Iib-	Input Bias Current	$V_{cm} = 15V$			-1	1	nA	1

Note 1: Parameter tested go-no-go only.

Note 2: Guaranteed parameter not tested.

Note 3: Datalog in K = V/mV.

Note 4: Calculated parameter for Class "S" only.

Rochester Electronics guarantees performance of its semiconductor products to the original OEM specifications. "Typical" values are for reference purposes only. Certain minimum or maximum ratings may be based on product characterization, design, simulation, or sample testing. Rochester Electronics reserves the right to make changes without further notice to any specification herein.