


Specifications		Notes
Connector Type	N Female	* Switching Functions: When the knob points to the center (Ground) switch position all antenna circuits are internally disconnected and grounded. When the knob is in an active position the unused antenna ports are grounded. The active position circuit is continuously protected by the replaceable cartridge.
Impedance	50 (Ohms)	
Frequency Range	DC-1 GHz	
VSWR	1.1:1 @ 30 MHz 1.3:1 @ 150 MHz 1.4:1 @ 450 MHz 1.6 :1 @ 1 GHz	
Insertion Loss	.1 dB @ 30 MHz .15 dB @ 150 MHz .5 dB @ 450 MHz .6 dB @ 1 GHz	
Power Handling Watts RF	500 WATTS MAX.	* Replaceable Cartridge
No. of Output Ports	4	
Isolation	50 dB	



PASTERNAK ENTERPRISES, INC.
 P.O BOX 16759, IRVINE, CA 92623
 PHONE (949) 261-1920 FAX (949) 261-7451
 WEB ADDRESS: www.pasternack.com
 E-MAIL ADDRESS: sales@pasternack.com
COAXIAL & FIBER OPTICS

DWG TITLE

PE7140

DES. N FEMALE, MANUAL COAX SWITCH WITH SURGE PROTECTOR

REV. B	FSCM NO. 53919	CAD FILE 082012	SCALE N/A	SIZE A	2233
--------	----------------	-----------------	-----------	--------	------

NOTES:
 1. UNLESS OTHERWISE SPECIFIED ALL DIMENSIONS ARE NOMINAL.
 2. ALL SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT NOTICE AT ANY TIME.
 3. DIMENSIONS ARE IN INCHES [mm].