


Power Transformers Fully Enclosed 4808 - 4820





LOW VOLTAGE RECTIFIER Transformers with fully enclosed vertical end covers.

- Primary voltage, 115 Volts, 60 Hz.
- Primary and secondary leads 8-10" long.
- 4-hole vertical mounting.
- 13 sizes are available, covering the range: 100 to 500 VA.
- CSA listed (LR 47366).



MECHANICAL



Dimensions, Inches

P/N	DIMENSIONS			D	E	F	G
	L	W	H				
4808	3.13	3.63	3.81	2.50	2.44	0.390	0.203
4809	3.13	3.88	3.81	2.50	2.69	0.390	0.203
4810	3.13	4.13	3.81	2.50	2.94	0.390	0.203
4811	3.13	4.38	3.81	2.50	3.19	0.390	0.203
4812	3.13	4.63	3.81	2.50	3.44	0.390	0.203
4813	3.75	4.50	4.56	3.00	3.44	0.375	0.187
4814	3.75	4.75	4.56	3.00	3.69	0.375	0.187
4815	3.75	5.00	4.56	3.00	3.94	0.375	0.187
4816	3.75	5.25	4.56	3.00	4.19	0.375	0.187
4817	3.75	5.50	4.56	3.00	4.44	0.375	0.187
4818	3.75	5.75	4.56	3.00	4.69	0.375	0.187
4819	3.75	6.00	4.56	3.00	4.94	0.375	0.187
4820	3.75	6.25	4.56	3.00	5.19	0.375	0.187

ELECTRICAL SPECIFICATION

Part No.	Secondary Voltages (A-A)		
	F.L. Volts	N.L. Volts	Current Amps
4808-01	6.3	6.75	16.00
4808-02	7.5	8.10	15.00
4808-03	11.0	11.80	10.00
4808-04	20.0	21.00	5.00
4808-05	36.0	37.90	3.00
4808-06	55.0	58.50	2.00
4808-07	60.0	64.00	2.00
4809-01	12.6	13.20	10.00
4809-02	25.0	27.20	5.00
4810-01	30.0	31.40	5.00
4811-01	5.0	5.30	30.00
4811-02	7.5	8.00	21.00
4811-03	11.0	11.70	15.00
4811-04	18.0	18.80	10.00
4811-05	36.0	38.20	5.00
4811-06	70.0	73.00	2.00
4811-07	80.0	82.70	2.00
4812-01	60.0	62.20	3.00
4813-01	50.0	51.80	5.00

Part No.	Secondary Voltages (A-A)		
	F.L. Volts	N.L. Volts	Current Amps
4814-01	12.6	13.00	20.00
4814-02	18.0	18.80	15.00
4814-03	22.0	22.30	12.00
4814-04	25.0	26.10	10.00
4814-05	30.0	31.40	10.00
4814-06	50.0	51.80	5.00
4814-07	200.0	212.00	0.87
4815-01	36.0	37.40	8.00
4815-02	70.0	72.00	4.00
4816-01	60.0	62.00	5.00
4816-02	80.0	82.50	4.00
4817-01	20.0	21.40	16.00
4818-01	18.0	18.50	20.00
4819-01	36.0	38.00	12.00
4820-01	22.0	22.50	20.00
4820-02	100.0	103.70	5.00

ISSUE: C 4808.CHP 950712